Network port connection method for GG-AT 60P printer

Step 1. Open the network port connection tool

GPrinter SettingTool1.0.0.2.exe	2022/2/23 15:56
IPAddressControlLib.dll	2022/1/20 13:52
🚳 libUsbContorl.dll	2022/1/20 13:52
🚳 RestSharp.dll	2022/1/20 13:51

Connect printer and PC with USB cable, click Find USB, choose USB01, click Ethernet setting. Enter the IP address , the IP address is idle, Set this IP address to the new IP address of the printer

A Drinker Catting T		
File Developed(D)		
File Download(D)	Language(L) Help(H)	
USB N	one V Find USB O Driver GG-TD1200C	
O Parallel	↓ ○ Ethernet 192.168.123.100	✓ Find Printer
О СОМ С	DM1 V 19200 V Find COM Local IP: 10.10.130.77	
Basic	TCP/IP Setting IP Address: 192 . 168 . 123 . 200 Set New IP	
Function	Set New MAC Set New MAC 4	
1 ¹⁰⁸	UDP Setting	
Ethernet	Enable DHCP and Timeout: 30 (Timeout: 14~90 s)	
Setting	IP Addres 192 . 168 . 123 . 200 Ping IP	
2	NetMask: 255 . 255 . 255 . 0 Result: 3	~
Advance Mode	GateWay: 192 . 168 . 123 . 1	Find Printer

Step 2. Open the printer property page, choose ports, click add port.

Font	s	Tools		Abou	,t
General	Sharing Ports	Advanced	Color Mar	nagement	Secu
Ni S	nestar GG-AT 60P	,		See.	8330
Print to the f checked por	ollowing port(s). Do t. Description	cuments will pr	int to the f	first free	
E LPT3:	Printer Port	~	SO		
COM1:	Serial Port				
COM2:	Serial Port				
COM3:	Serial Port				
COM4:	Serial Port				
FILE:	Print to File				
USB059	USB 虚拟打印机算	i Nin	estar GG	-AT 60P	
Add F	Por <u>t</u>	Delete Port		<u>C</u> onfigure l	Port
Enable bio	directional support				
Enable pri	nter pooling				
LIIODIC DI				20	

Step 3. Choose standard TCP/IP port, choose new port, enter the IP address and port name. The IP address corresponds to the IP address read by the tool. Click next until finished.

Eanta	Too		About	
Printer Ports		-		
Available port types: Adobe PDF Port Mon	itor		1.08.0 ²	
Standard TCP/IP Port			20r	
New Port Type		New <u>P</u> ort	Cancel	
COIVIS: Serial Port				
COM4: Serial Port				
I FILE: Print to Fil	e T印机端口	Ninester GG-	AT 600	
030039 030 (<u>200</u>)		Nillestal 00%	AT OOP	Ŧ
Add Por <u>t</u>	<u>D</u> elete	Port	<u>C</u> onfigure Port]
Fnable bidirectional su	upport			,
Enable printer pooling	, pport			
S ²	'		2022-0-	
	ОК	Cancel		Help
		-O.		

Add Standard TCP/IP Printer Port Wizar Add port For which device do you want to ad	d dd a port?	
Enter the Printer Name or IP ad Printer Name or IP <u>A</u> ddress:	Idress, and a port name fo	r the desired device.
Port Name:	10.11.120.197	0220803
		< Back Next > Cancel

In connection process, it will show that the device could not be identified, click next. Driver connection is completed.

The device could not b	e identified	
224	o looi kiiloo.	
		Nº0
Q		0.
The device is not found o	on the network. Be sure that:	
0.1	S.	
1. The device is turned o	on	
2. The network is conne	cted.	
3. The device is properly	/ configured.	
4. The address on the pr	revious page is correct.	
If you think the address is	s not correct, click Back to return to t	he previous page. Then correct the
address and perform and	ther search on the network. If you a	re sure the address is correct, select the
address and perform and device type below.	other search on the network. If you a	re sure the address is correct, select the
address and perform and device type below. Device Type	other search on the network. If you a	re sure the address is correct, select the
address and perform and device type below. Device Type	other search on the network. If you a	re sure the address is correct, select the
address and perform and device type below. Device Type	other search on the network. If you a ric Network Card	re sure the address is correct, select the
address and perform and device type below. Device Type <u>S</u> tandard Gene	ric Network Card	re sure the address is correct, select the
address and perform and device type below. Device Type <u>S</u> tandard <u>C</u> ustom <u>Se</u>	ric Network Card	re sure the address is correct, select the
address and perform and device type below. Device Type Standard Gene <u>Custom</u> S <u>e</u>	ric Network Card	re sure the address is correct, select the

After the connection is successful, it can print normally.